

# WINEGARD®

## Movin' View™ Upgrade Kit MV-1202 Second Receiver for Models MV-0055/MV-1111

**MV-1202 enables use of two receivers with MV-1111**

**Use of two receivers with MV-0055 requires this kit plus MV-2000 Kit**

**UPGRADE FOR MV-0055:** First disconnect the coax cable from the SAT IN connection on the receiver. Then follow steps 1 through 5.

**UPGRADE FOR MV-1111:** First disconnect the coax cable from DEMULTIPLEXER D575p input connection, then follow steps 1 through 5.

### Connecting first receiver:

1. Connect coax cable from roof to the "IN" input on the splitter (SP-2052). Connect a coax cable from one of the "OUT" ports or jack on the splitter (SP-2052). Connect other end of this cable to "input" on the DC PASSIVE D575p demultiplexer.
2. Determine primary receiver. This is the one used most often, and controls the toggle feature.
3. Connect a coax cable from the "satellite receiver" output on the DC PASSIVE D575p demultiplexer. Connect the other end of this cable to "Satellite IN" on the primary receiver.

### Connecting the second receiver:

4. Connect coax cable from the other "OUT" output on the splitter (SP-2052). Connect the other end of this cable to the "input" on the DC BLOCK demultiplexer.
5. Connector a coax cable from the "receiver" output on the DC BLOCK demultiplexer. Connect the other end of this cable to "Satellite IN" on the secondary receiver.

**Demultiplexer is included with MV-1111. Demultiplexer NOT INCLUDED with MV-0055.**

